

Model	D8-A01S
Frequency range	DC - 4000 MHz
Insertion Loss	18 dB nominal
Isolation	17 dB Min.
Input Return Loss	18 dB Min.
Amplitude Balance	± 0.2 dB
Phase Balance	± 5 degrees
Connectors	SMA female
Power	1 Watt



The Model D8-A01 is a broadband 8 way resistive type power divider/combiner. It is phase and amplitude balanced with low VSWR and ripple over the full band.

With the unique radial and symmetrical resistive circuit used, the basic design can readily be modified for any number of outputs, odd or even., within the same outline envelope.

The Model D8-A01 is available with Type N female connectors;

See Model D16-A01 for 16 way power divider with similar specifications.

Made in USA.

